

Surelight Field Installable SC Connector Kits



Product Description

The Surelight Field Installable Connector Series are pre polished, pre assembled connectors that can be installed on the job site within two minutes. These highly reliable low loss connectors are available in Singlemode and Multimode, APC and UPC. 900um, 2.0mm, and 3.0mm versions are available. They are reusable up to 5 times.

Applications

Fiber To The Home (FTTH)
Fiber Optic Telecommunication
Fiber Distribution Frame
Optical Cable Interconnection
Cable Television

General Specifications

Parameter	Specification
Standard:	TIA / EIA 604-10 (LC)
Insertion Loss:	Typical .3dB Max .5dB
Return Loss:	Typical 50dB Max 55dB (UPC) Typical 55dB Max 60dB (APC)
Durability:	≤ .3dB, 500 Matings
Tension:	≤ .2dB Change 3kg
Operating Temperature:	-40 °C to +75 °C

Ordering

SC Surelight Connector Kits	
Stock ID	Description
066-024-10	Singlemode SC/UPC Connector Blue Housing 9/125
066-025-10	Singlemode SC/APC Connector Green Housing 9/125
066-027-10	Multimode SC/UPC Connector Beige Housing 62.5/125 OM1
066-132-10	Multimode SC/UPC Connector Black Housing 50/125 OM4

2mm SC Surelight Connector Kits	
Stock ID	Description
066-223-10	Singlemode SC/UPC Connector Blue Housing 2mm
066-222-10	Singlemode SC/APC Connector Green Housing 2mm

3mm SC Surelight Connector Kits	
Stock ID	Description
066-215-10	Singlemode SC/UPC Connector Blue Housing 3mm
066-214-10	Singlemode SC/APC Connector Green Housing 3mm

Contact Us

North America	Europe, Middle East & Africa	Latin & South America
Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: engsupport@gomultilink.com	Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: engsupport@gomultilink.com	Tel: +1 954 499 9203 Mobile: +1 305 684 2388 Email: hquinones@gomultilink.com



Multilink Inc.
580 Ternes Ln
Elyria, OH 44035
Tel: (440) 366-6966
Fax: (440) 366-6802



facebook.com/GoMultilink



twitter.com/GoMultilink



youtube.com/GoMultilink

© Multilink Inc. 2015 All Rights Reserved

Contact Us

North America	Europe, Middle East & Africa	Latin & South America
Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: engsupport@gomultilink.com	Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: engsupport@gomultilink.com	Tel: +1 954 499 9203 Mobile: +1 305 684 2388 Email: hquinones@gomultilink.com