

BAxxx & BBxxx: 4" and 5" Boot Kits



A valmont  COMPANY



Features:

- One-piece design for easy installation and superior water-sealing properties
- Kits include rubber boot, one cushion insert, and two stainless steel hose clamps
- For use with our entry panels or tube entry
- Additional configurations can be made using barrel cushions with appropriate mating hanger size
- Blank boots can be used to seal unused ports or can be field cut for custom hole configurations
- For rooftop entries use SCS30 rubber sealer

Construction:

- Boot jacket and cushion insert are manufactured from EPDM rubber ; material meets ASTM-D2000 and SAE J200
- Hose clamps have 201 stainless steel band and housing with 305 stainless steel screw

Related Products:

- Entry panels, tube entry, cushion inserts, cushion plugs, barrel cushions

created on: 07/07/2023

BAxxx & BBxxx: 4" and 5" Boot Kits



A valmont COMPANY

Coax Cables

Part #		Cable Size & Type	# of Holes	Weight	
4"	5"			4"	5"
BA143F	BB143F	1/4" Flex Coax	3	1.4 lb	2.0 lb
BA38	BB38	3/8" Coax	1	1.4 lb	2.0 lb
BA384	BB384	3/8" Coax	4	1.4 lb	2.0 lb
BA12FLX	BB12FLX	1/2" Flex Coax	1	1.4 lb	2.0 lb
BA124FLX	BB124FLX	1/2" Flex Coax	4	1.4 lb	2.0 lb
BA12	BB12	1/2" Foam Coax	1	1.4 lb	2.0 lb
BA122	BB122	1/2" Foam Coax	2	1.4 lb	2.0 lb
BA123	BB123	1/2" Foam Coax	3	1.4 lb	2.0 lb
BA124	BB124	1/2" Foam Coax	4	1.4 lb	2.0 lb
BA129	BB129	1/2" Foam Coax	9	1.4 lb	2.0 lb
BALR94	BBLR94	5/8" Coax	4	1.4 lb	2.0 lb
BA78	BB78	7/8" Coax	1	1.4 lb	2.0 lb
BA782	BB782	7/8" Coax	2	1.4 lb	2.0 lb
BA783	BB783	7/8" Coax	3	1.4 lb	2.0 lb
BA784	BB784	7/8" Coax	4	1.4 lb	2.0 lb
BA114	BB114	1-1/4" Coax	1	1.4 lb	2.0 lb
BA158	BB158	1-5/8" Coax	1	1.4 lb	2.0 lb
BA214	BB214	2-1/4" Coax	1	1.4 lb	2.0 lb
BAZERO	BBZERO	Blank, No Holes	-	1.4 lb	2.0 lb

Mixed Coax

Part #		Cable Size & Type	# of Holes	Weight	
4"	5"			4"	5"
BA121M	BB121M	(1) 1/2" Foam Coax & (2) 7/8" Coax	3	1.4 lb	2.0 lb
BA122M	BB122M	(2) 1/2" Foam Coax & (1) 7/8" Coax	3	1.4 lb	2.0 lb
BA123M	BB123M	(3) 1/2" Foam Coax & (2) 7/8" Coax	5	1.4 lb	2.0 lb

BAXXX & BBXXX: 4" and 5" Boot Kits



A valmont COMPANY

LMR Cables

Part #		Cable Size & Type	# of Holes	Weight	
4"	5"			4"	5"
BALR24	BBLR24	LMR-240	4	1.4 lb	2.0 lb
BALX4	BBLX4	LMR-400, 3/8" Flex, & RG11U	1	1.4 lb	2.0 lb
BALR42	BBLR42	LMR-400, 3/8" Flex, & RG11U	2	1.4 lb	2.0 lb
BALR44	BBLR44	LMR-400, 3/8" Flex, & RG11U	4	1.4 lb	2.0 lb
BALR94	BBLR94	LMR-900	4	1.4 lb	2.0 lb

Elliptical Waveguide

Part #		Cable Size & Type	# of Holes	Weight	
4"	5"			4"	5"
BAEW43	BBEW43	EW43	1	1.4 lb	2.0 lb
BAEW52	BBEW52	EW52, EWP52, WE61	1	1.4 lb	2.0 lb
BAEW63	BBEW63	EW63, EWP63, WE65	1	1.4 lb	2.0 lb
BAEW632	BBEW632	EW63, EWP63, WE65	2	1.4 lb	2.0 lb
BAEW77	BBEW77	EW77 & EWP77	1	1.4 lb	2.0 lb
BAEW772	BBEW772	EW77 & EWP77	2	1.4 lb	2.0 lb
BAEW90	BBEW90	EW90 & EWP90	1	1.4 lb	2.0 lb
BAEW903	BBEW903	EW90 & EWP90	3	1.4 lb	2.0 lb
BAEW180	BBEW180	EW180, EWP180, WE190 & WE191	1	1.4 lb	2.0 lb

Rectangular Waveguide

Part #		Cable Size & Type	# of Holes	Weight	
4"	5"			4"	5"
BAWR75	BBWR75	WR75	1	1.4 lb	2.0 lb
BAWR90F	BBWR90F	WR90 Flex	1	1.4 lb	2.0 lb
BAWR137	BBWR137	WR137	1	1.4 lb	2.0 lb
BAWR137F	BBWR137F	WR137 Flex	1	1.4 lb	2.0 lb