

Reverse Equalizer, 42 MHz, MEQ



For Broadband International® 2PAC-C Line Extender, C-COR® Flex Max 901 Trunk and Bridger, Flex Max 900, Flex Max 331, Flex Max 340, Flex Net 800, Flex Net 700, E900 and E700.

PARAMETER	SPECIFICATION	Unit
Passband	5-42	MHz
Flatness	+/- 0.4	dB
Insertion Loss (Max)	1	dB
Return Loss	-18	dB

42 MHz Slope Chart – Frequency vs. Insertion Loss

OEM Model Number	BBI Part Number	Value	Slope	5	10	20	30	40	42
162290-00	620000	0 dB	0.0	0.0	0.0	0.0	0.0	0.0	0.0
162395-01	620401	1 dB	1.1	1.3	1.2	1.0	0.7	0.2	0.2
162395-02	620402	2 dB	2.1	3.0	2.8	2.1	1.4	1.0	0.9
162395-03	620403	3 dB	3.1	4.0	3.5	2.6	1.7	1.0	0.9
162395-04	620404	4 dB	4.0	5.0	4.2	3.1	1.9	1.1	1.0
162395-05	620405	5 dB	5.0	5.9	5.1	3.6	2.1	1.0	0.9
162395-06	620406	6 dB	5.9	6.9	6.0	4.3	2.5	1.1	1.0
162395-07	620407	7 dB	7.0	8.2	7.0	4.9	2.9	1.4	1.2
162395-08	620408	8 dB	7.8	8.3	7.0	4.6	2.0	0.6	0.4
162395-09	620409	9 dB	8.9	9.4	7.9	5.2	2.2	0.7	0.5
162395-10	620410	10 dB	9.8	10.4	8.7	5.5	2.3	0.8	0.6
162395-11	620411	11 dB	10.9	11.7	9.8	6.4	3.3	1.2	0.8
162395-12	620412	12 dB	11.9	12.9	10.7	6.9	3.5	1.3	1.0